

Display type: Sharp LQ9PS01
 Cable no.: Not available
 System: 486LCD with FPUM-1
 Display driver:SHA LQ10DS01
 Status: Verified

Display (41-pole conn.)		Cable	JPLCD	connector	Remarks
Pin no.	Function	Wire no.	Pin	Function	
1	GND	1	12	GND	
2	CLK	2	13	SHFCLK	Dot clock
3	GND	3	14	GND	
4	GND	4	9	GND	
5	Hsync	5	10	LP	
6	Vsync	6	11	FLM	
7	GND	7	6	GND	
8	R0	8	32	GND	
9	R1	9	31	P11	
10	R2	10	33	P12	
11	R3	11	34	P13	
12	R4	12	36	P14	
13	R5	13	37	P15	
14	GND	14	35	GND	
15	GND	15	35	GND	
16	GND	16	23	GND	
17	G0	17	22	P5	
18	G1	18	24	P6	
19	G2	19	25	P7	
20	G3	20	27	P8	
21	G4	21	28	P9	
22	G5	22	30	P10	
23	GND	23	23	GND	
24	GND	24	26	GND	
25	GND	25	26	GND	
26	B0	26	17	GND	
27	B1	27	15	P0	
28	B2	28	16	P1	
29	B3	29	18	P2	
30	B4	30	19	P3	
31	B5	31	21	P4	
32	GND	32	20	GND	
33	GND	33	20	GND	
34	GND	34	29	GND	
35	ENAB	35	7	M	
36	VCC	36	1	VCC	
37	VCC	37	2	VCC	
38	R/L	38	29	GND	Horizontal selection
39	TST	39	-	-	No connection
40	GND	40	38	GND	
41	GND	41	38	GND	