

Display type: IBM ITSX80F with Adapt80F  
 Inverter no.: not available  
 Cable no.: not available  
 System: 686LCD  
 Display driver: 1280x1024, TFT Color, IBM, ITSX80F 2x12 E, 5V  
 Status: Verified

Adapt80F	PL1	JPLCD	50-pole conn.	Remarks
Function	Pin	Pin	Function	
GND	1	38	GND	
RE2	2	38	GND	
RO2	3	38	GND	
GND	4	38	GND	
RE3	5	38	GND	
RO3	6	38	GND	
GND	7	-	nc	
RE4	8	46	P20	
RO4	9	41	P16	
GND	10	45	GND	
RE5	11	47	P21	
RO5	12	42	P17	
GND	13	45	GND	
RE6	14	48	P22	
RO6	15	43	P18	
GND	16	50	GND	
RE7	17	49	P23	
RO7	18	44	P19	
GND	19	50	GND	
GE2	20	23	GND	
GO2	21	23	GND	
GND	22	-	nc	
GE3	23	26	GND	
GO3	24	26	GND	
GND	25	-	nc	
GE4	26	33	P12	
GO4	27	27	P8	
GND	28	29	GND	
GE5	29	34	P13	
GO5	30	28	P9	
GND	31	29	GND	
GE6	32	36	P14	
GO6	33	30	P10	
GND	34	32	GND	
GE7	35	37	P15	
GO7	36	31	P11	
GND	37	32	GND	
BE2	38	35	GND	
BO2	39	35	GND	
GND	40	-	nc	
BE3	41	35	GND	
BO3	42	35	GND	
GND	43	20	GND	
BE4	44	21	P4	
BO4	45	15	P0	

GND	46	20	GND
BE5	47	22	P5
BO5	48	16	P1
GND	49	17	GND
BE6	50	24	P6
BO6	51	18	P2
GND	52	17	GND
BE7	53	25	P7
BO7	54	19	P3
GND	55	6	GND
GND	56	6	GND
VDD Panel	57	1	VCC
VDD Panel	58	1	VCC
VDD Panel	59	2	VCC
VDD Panel	60	2	VCC

Adapt80F	PL2	JPLCD	50-pole conn.	Remarks
Function	Pin	Pin	Function	
GND	1	12	GND	
DTCLK	2	13	SHFCLK	
GND	3	14	GND	
nc	4	-	-	
GND	5	9	GND	
HSYNC	6	10	HSYNC	
GND	7	9	GND	
VSYNC	8	11	VSYNC	
GND	9	-	-	
DTMG	10	7	M	
GND	11	-	-	
nc	12	-	-	
GND	13	--	-	
nc	14	-	-	
GND	15	-	-	
PENA	16	8	GPO1	